



Dal 1965 il SELECO offre al mercato italiano innovazione tecnologica conquistando negli anni una grandissima notorietà seguita da numerosi riconoscimenti nel mondo per qualità e profilo estetico. Fin dagli anni 80 SELECO è stata particolarmente attiva nell'ambito delle sponsorizzazioni in campo sportivo ed è diventato main sponsor di importanti squadre di calcio, pallacanestro e anche pallavolo.


Oggi SELECO torna sul mercato, l'obiettivo è rimasto immutato nel tempo... essere il migliore!

39 SMART TV

Modello **TV39020HDA9SMART**
 Tipologia **SMART TV Android 9.0**
 Ean Code **8057158460882**



Il SELECO SMART TV 39 è il miglior compromesso sia per una camera da letto che per una cucina o ancora per una seconda casa. Con il TV SMART SELECO da 39 pollici con la sua semplicità d'uso può sfruttare i contenuti su internet. Grazie ai 3 ingressi HDMI è possibile connettere al TV SELECO la tua console gioco, un lettore DVD o qualsiasi altro device. La doppia porta USB ti permette di condividere le tue foto o video sullo schermo.



Pannello A+ Cell - 100% Zero Pixel Problem

| | | | | |
|---------------------------|---|--|---|--|
| MAINBOARD | 13AT204 | | | |
| OSD LANGUAGE | 32 OSD LANGUAGES | | | |
| | English, Turkish, Arabic, Spanish, Italian, German, French, Hungarian, Russian, Serbian, Croatian, Greek, Bulgarian, Albanian, Romanian, Macedonian, Portuguese, Estonian, Bosnian, Latvian, Lithuanian, Czech, Danish, Polish, Dutch, Norwegian, Persian, Slovak, Slovenian, Finnish, Swedish, Ukrainian | | | |
| PANEL | Panel Type | LED | | |
| | Size | 39" | | |
| | Luminance | 250 cd/m2 (Typical) +/- %10 | | |
| | Max Resolution | 1366 x 768 | | |
| | Viewing Angle | 178° | | |
| PROCESSOR | CPU | ARM Cortex-A55 Quad-Core | | |
| | GPU | Mali470MP2 | | |
| MEMORY | RAM | 1G byte | | |
| | ROM | 8G byte | | |
| OPERATING SYSTEM | ANDROID P(9.0) | | | |
| SMART APPLICATIONS | Pre-Installed | App Store, Weather, Miracast | | |
| | Launcher Highlighted | Chrome, NetFlix, Facebook, Spotify, YouTube, and any other main APPS | | |
| | Web Browser | Chrome | | |
| TV | ATV | Receiving Range | 44MHz ~ 870MHz | |
| | | Input Impedance | 75Ω | |
| | | Video System | PAL, SECAM | |
| | | Sound System | BG, DK, I | |
| | | Max Storage Channels | 256 | |
| | DVB-S/S2 | Modulation | COFDM 2K/8K, QPSK,8PSK | |
| | | LNB Power | Auto/13V/18V/OFF Out put 500mA@Max | |
| | | LNB Switch Control | 22KHz | |
| | | DiSEqC Version | 1.0 / 1.1/1.2 compatible | |
| | | Receive Channel | (dvbc+dvbt+dvbs<=10000) | |
| | DVB-T | Modulation | COFDM 2K/8K, QPSK,16QAM, 64QAM | |
| | | Receive Channel | 2000 | |
| | DVB-T2 | Modulation | QPSK, 16QAM, 64QAM, 256QAM | |
| | | Receive Channel | 2000 | |
| | DVB-C | Modulation | 16QAM, 64QAM, 128QAM, 256QAM | |
| Receive Channel | | 2000 | | |
| VIDEO SYSTEM | MPEG-1,MPEG-2,MPEG-4,H.264,VC1,VP8/9,MJPEG,H.265,AVS,AVS+, | | | |
| AUDIO SYSTEM | MPEG,PCM,ADPCM,FLAC,VORBIS,APE,AC3(* Need Dolby chip support) MP3,WAV,MKA,OGG,APE | | | |
| VIDEO INPUT | HDMI | 480i, 480p, 720p, 1080i, 1080p | | |
| | Component | 480i, 480p, 720p, 1080i, 1080p | | |
| | | Video System | PAL/NTSC | |
| | AV | Video Level | 1.0 Vp-p±10% | |
| AUDIO INPUT | AV/Component Audio | Mini RCA Input | 0.2 ~ 2.0 VRMS | |
| AUDIO OUTPUT | Frequency Response | 100Hz-15KHz @±3dB(1KHz 0dB reference signal) | | |
| | Max Output Power | 2×8W(8Ω)/2×10W(6Ω) THD+N<10%@1KHz for (Audio Input: 0.5VRMS) | 2×8mW (32Ω) THD+N<10%@1KHz for Headphone | |
| WEAK SIGNAL ENHACEMENT | YES | | | |
| NOISE REDUCTION | YES | | | |
| KEY FUNCTION | STANDBY | | | |
| ENERGY SAVING | YES | | | |
| STANDBY POWER CONSUMPTION | 0.4W | | | |
| BLUETOOTH | NO (Optional) | | | |
| HOTEL MODE | YES (Optional) | | | |
| INTERNET CONNECTIVITY | ETHERNET 10/100M auto-identification and DHCP Internal WI-FI (IEEE 802.11b/g/n) | | | |
| TERMINALS | INPUT | HDMI | 3 x HDMI Connector | |
| | | USB | 2 x USB 2.0 (NO PVR – USB RECORDIG FEATURE NOT AVAILABLE) | |
| | | Component | 1 x Mini RCA Connector (Black) | |
| | | AV Video + AV Audio | 3 x RCA Connector +1 x Mini RCA Connector (Black) | |
| | | CI Slot | 1 x CI Slot (Black) | |
| | OUTPUT | ETHERNET | 1 x RJ45 | |
| | | VGA | 1 x VGA | |
| | | DTV & ATV (Optional) VGA AUDIO IN | 1 x RF-Connector 1 x Mini RCA Connector (Black) | |
| | | Satellite TV (Optional) | 1 x F-Connector | |
| | | Headphone (Earphone) | 1 x Mini RCA Connector (Black) | |
| SPDIF | 1 x Optical (Optional) | | | |